

# FLOS

60.9222

**Continuous current power supply of 12-20W, 110/240V - 50/60Hz with power current selected through adjustable 250mA - 12W / 350mA - 17W / 400mA - 19W / 450 / 500/ 550 / 600 / 700mA - 20W regulable Dali 1 & Dali 2**



110V = Max 15W.

Are you a professional and your project needs consulting and support?

[BOOK AN APPOINTMENT](#)

## Main specifications

Environments Indoor dry location

Power (W) 20

## Physical


Trim No

Bezel diameter (mm) 55


Length (mm) 108

Net weight (kg) 0.11

IP internal 20



## Ecodesign and Energy Labelling



Replaceable control gear by a professional



<https://professional.flos.com/en/global/product/continuous-current-power-supply-of-12-20w-110-240v-50-60hz-with-power-current-selected-through-adjustable-250ma-12w-350ma-17w-400ma-19w-450-500-550-600-700ma-20w-regulable-dali-1-dali-2-60.9222/>

60.9222

©2022 Flos - P.IVA 00290820174 - 12/23/2024

professional.flos.com | info@flos.com 1/2

In our constantly evolving world and business, technical upgrades happen every day. This means all product specifications and data are subject to change without warning in order to improve reliability, function, performance or otherwise. We make every effort to ensure the accuracy of our product images, however due to different lighting and screens used for viewing, the colours may vary. Images are indicative of the quality and style of the product but may not represent the precise details of the product you receive. This is because we are constantly working to make improvements. For aesthetic reasons, cables and/or electrical elements are often not shown. Refer to technical data sheets for all technical data. Images and colours are not part of any contract or warranty in any way.

## Photometric

## Electrical

Extreme cut off	No	Insulation class	II
		Main voltage (Vac)	110-240
		LED current (mA)	250 / 350 / 400 / 450 / 500 / 550 / 600 / 700
		Dimmable	Yes
		Power supply type	Dimmable DALI 2, Dimmable DALI 1
		Dimming range (%)	1-100
		Precabled	No
		Emergency	Yes
		Batteries inside	No

## Notes

Default dimming AM+PWM: 1-25% PWM 2 kHz+25-100% AM.

Full AM DIMMING: 1 - 100%. Active Power Factor Corrector.

Input and output terminal blocks on the same side

(wire cross-section up to 1,5 mm<sup>2</sup> / AWG15).